

Installation Instructions

36 Sensor BilgAlarm™ Fail-Safe System

Model No. BA36FST-2W12V

The following parts are enclosed:



1 BilgAlarm Panel



36 Sensors with 40 foot - 2 Conductor Cables



4 Panel Mounting Screws
72 Sensor Bracket Mounting Screws
36 Sensor Bracket Set Screws
2 Siren Mounting Screws



36 Sensor Brackets



1 Siren

*The most common installation screws are included. Since each installation is different and may require different types and lengths of wood screws, machine screws, washers, lock washers, and nuts, please purchase the screws that are applicable for your installation at your local marine store. Stainless steel screws are recommended.

STEP 1

Mount Control Panel, Sensors, and Siren

Control Panel

Carefully cut a rectangular hole (width) 5.7 inches X (height) 8.9 inches to mount the BilgAlarm™ Control Panel. Inspect carefully behind where you intend to cut to avoid damage to other equipment and provide adequate room for installation of the BilgAlarm™ Control Panel and wiring. Do not cut the hole larger than 5.7 inches X 8.9 inches. The thickness of the mounting surface must not be more than $\frac{3}{4}$ inch. Secure the BilgAlarm™ Control Panel with 4 screws after electrical connections have been made.

Sensors

BilgAlarm™ Sensors are placed vertically (cable end up) where water collects, which is usually where the bilge pumps are located. Place a BilgAlarm™ Sensor 2 to 3 inches above the bilge water level at which the bilge pump normally turns on. Should the pump not turn on or is unable to handle the volume of water coming in, the BilgAlarm™ system will sound an early warning alarm. Repeat installation of the remaining BilgAlarm™ Sensors and run sensor cables back to the BilgAlarm™ Control Panel. Special mounting brackets and mounting screws are provided to attach the sensors. A set screw is provided to secure the sensor to the mounting bracket and to adjust sensor height, if desired. Screw the set screw through any side of the sensor bracket until the sensor is secure.

Siren

Mount the warning siren near the control panel in an unobstructed location. Run the leads back to the BilgAlarm™ Control Panel. Siren leads may be extended, as required.

Continued On Next Page

STEP 2

Wire Sensors, Siren to the Control Panel

Model BA36FST-2W12V

		STBD		PORT			
21	⊖	Red	Sensor 2	Sensor 1	Red	⊖	11
22	⊖	Black			Black	⊖	12
41	⊖	Red	Sensor 4	Sensor 3	Black	⊖	31
42	⊖	Black			Red	⊖	32
61	⊖	Red	Sensor 6	Sensor 5	Red	⊖	51
62	⊖	Black			Black	⊖	52
81	⊖	Red	Sensor 8	Sensor 7	Red	⊖	71
82	⊖	Black			Black	⊖	72
101	⊖	Red	Sensor 10	Sensor 9	Red	⊖	91
102	⊖	Black			Black	⊖	92
121	⊖	Red	Sensor 12	Sensor 11	Red	⊖	111
122	⊖	Black			Black	⊖	112
141	⊖	Red	Sensor 14	Sensor 13	Red	⊖	131
142	⊖	Black			Black	⊖	132
161	⊖	Red	Sensor 16	Sensor 15	Red	⊖	151
162	⊖	Black			Black	⊖	152
181	⊖	Red	Sensor 18	Sensor 17	Red	⊖	171
182	⊖	Black			Black	⊖	172
201	⊖	Red	Sensor 20	Sensor 19	Red	⊖	191
202	⊖	Black			Black	⊖	192
221	⊖	Red	Sensor 22	Sensor 21	Red	⊖	211
222	⊖	Black			Black	⊖	212
241	⊖	Red	Sensor 24	Sensor 23	Red	⊖	231
242	⊖	Black			Black	⊖	232
261	⊖	Red	Sensor 26	Sensor 25	Red	⊖	251
262	⊖	Black			Black	⊖	252
281	⊖	Red	Sensor 28	Sensor 27	Red	⊖	271
282	⊖	Black			Black	⊖	272
301	⊖	Red	Sensor 30	Sensor 29	Red	⊖	291
302	⊖	Black			Black	⊖	292
321	⊖	Red	Sensor 32	Sensor 31	Red	⊖	311
322	⊖	Black			Black	⊖	312
341	⊖	Red	Sensor 34	Sensor 33	Red	⊖	331
342	⊖	Black			Black	⊖	332
361	⊖	Red	Sensor 36	Sensor 35	Red	⊖	351
362	⊖	Black			Black	⊖	352
				Siren	Red	⊖	+
				12 VDC	Black	⊖	-
				Power	Pos	⊖	+
				12 VDC	Neg	⊖	-

Sensors

Attach the two leads of each sensor to the appropriate sensor terminal strip. The terminals are marked for each sensor. See wiring diagram to the left. Be sure to put the proper color wire in the proper terminal strip hole. Tighten securely, but do not over tighten.

Siren

Attach the two leads of the siren to the control panel paying attention to polarity. See wiring diagram to the left. Be sure to connect the red and black wires correctly. Tighten securely, but do not over tighten.

Note: Additional sirens and an optional strobe light may also be added, as long as the total load does not exceed the BilgAlarm™ two ampere (2 AMP) rated output.

Strobe Light (Optional)

Attach the two leads of the strobe light to the siren terminals on the control panel, paying attention to polarity. Connect the negative lead (black) to - and the positive lead (red) to + on the siren output terminal strip. The strobe light will turn off if the siren is muted, but the bilge warning light will continue to flash until all bilge warnings have been corrected.

STEP 3

Connecting Power to the Control Panel & Testing System

Attach power leads (12VDC)

Attach the power leads to the control panel, paying attention to polarity. See wiring diagram above. When power is first applied, the siren will sound for five seconds. You may press the **Mute** button to silence the siren.

Test your system

Test your system now by pressing and holding the **Test** button and then pressing the **Mute** button after the siren turns on. To reset the mute condition, just release the **Test** button and the alarm will reset when the bilge warning light turns off after 5 seconds. You can also test your system by putting a cup of water under a sensor or just placing a wet rag across the sensor electrodes.

To test silently

Press and hold the **Mute** button before depressing the **Test** button. The only sound will be a brief “chirp” when the alarm resets. This completes the installation of your new BilgAlarm™ Early Warning System.

Operating Notes:

The BilgAlarm™ fail-safe, high bilge water warning system is designed to minimize “nuisance alarms” from splashing and sloshing/slopping bilge water in commercial fishing boats and other commercial vessels. Water must be continuously present at a sensor for five seconds for the siren to sound. Conversely, water must be absent from all sensors for five seconds for the **Mute** button to reset. A **RED LED** alarm indicates high bilge water or a shorted sensor cable. A **GREEN LED** alarm indicates an open sensor cable. All alarm systems should be periodically tested to assure that they're functional and that power is present to the system.

To the Installer:

Below is some additional information you may find useful:

Sensors

Each sensor comes with a 40 foot cable. You may shorten it. If you would prefer a longer length, please contact our office. For reliability and longevity of the system, please don't make splices in the sensor cables, especially within the bilge area.

Sensor Installation

Sometimes it's easier to add a pull line through a span that's hard to run cables/wires. A pull line is a line that's twice as long as the span, so you can pull wires in either direction without losing the ends of the line. Secure the ends of the line so they can't be pulled through accidentally. When the task is accomplished, leave the line for the next cable pull. (Nylon clothesline works well)

Splicing Wire

We offer continuous sensor cables to 1000 feet. If splicing of any wires is needed, it's best to take the time and solder the splices and then heat shrink wrap the connections or use specialized water-proof type connectors, or heat shrink crimp connectors. If an improperly wrapped sensor cable splice becomes wet, it will act as a BilgAlarm™ sensor

and will also set-off an alarm. BilgAlarm™ is not liable for any sensor cable that has been spliced, altered, or changed.